

Introducing the

# Acure



[www.sunsynk.com](http://www.sunsynk.com)  
[sales@sunsynk.com](mailto:sales@sunsynk.com)

SUN  SYNK

# Introducing the Sunsynk Acure

A game-changing energy management system ranging from 3.6kW to 12kW. Seamlessly optimise your power consumption with user-friendly features such as a programmable wireless smart switch, included 40 Amp switch for reliable distribution, and the ability to connect up to 10 smart switches for tailored efficiency. With built-in Bluetooth, Wi-Fi, and LAN connection, monitoring your energy usage has never been smoother. The new user interface enhances accessibility for users of all levels, while safety is prioritised with built-in arc fault detection and solar panel theft detection circuits.

The multi-colour LED strip offers real-time insights, and the system is compatible with Ridge Blade wind turbines, electric vehicles, and hot water tank control. In local mode, take personalised control, and during load shedding, the system can automatically shut down high loads.

Sunsynk Acure is the epitome of smart, efficient, and user-friendly power utilisation, ushering in a new era of energy management for your home.



## Optimise Your Energy

- **Programmable Wireless Smart Switch**  
40 Amp switch included.
- **Max. 10 Smart Switches**  
For max. power optimisation.
- **Wireless CT Coil**
- **Built-in Wi-Fi & Bluetooth**  
No Data Logger required.
- **Built-in Solar Panel Theft Detection Circuits**
- **Built-in Arc Fault Detection**
- **New User Interface**
- **Multi-Colour LED Status Bar**  
Indicating inverter status & SOC.
- **Ridge Blade Wind Turbine Compatible**





### Our Distributors

To see distributors in your area.

[www.sunsynk.org/ourdistributors](http://www.sunsynk.org/ourdistributors)





**Acure 3.6/5kW Ecco**  
Single-Phase Ecco Hybrid Inverter



SunC1-3.6LV01(W/B) / SunC1-5.0LV01(W/B)





**Acure 3.6/5/8kW**  
Single-Phase Hybrid Inverter



SunC2-3.6LV01(W/B) / SunC2-5LV01(W/B)  
/ SunC2-8.0LV01(W/B)



**Acure 5/8/12kW**  
Three-Phase Ecco Hybrid Inverter



SunC3-5.0LV03(W/B) / SunC3-8.0LV03(W/B)  
/ SunC3-10.0LV03(W/B) / SunC3-12.0LV03(W/B)



## Contact Us

---

**Email** sales@sunsynk.com

**Address UK** 17 Turnstone Business Park, Mulberry Avenue, Widnes, Cheshire, WA8 0WN

**HK** Units 702-704, 7/F Texwood Plaza, 6 How Ming Street, Kwun Tong, Kowloon, Hong Kong

**SA** 80 Highview Boulevard, Ferndale, Randburg, 2160, South Africa

**NL** Henri Wijnmalenweg 8, 5657 EP Eindhoven, Netherlands

**AU** Level 1, 982-988 Wellington Street, West Perth WA 6005, Australia

**ES** Tafetana, 32 P.I. Las Andorriñas 38639 Las Chafiras Santa Cruz de Tenerife

**US** 100 S. Ashley Drive, Suite 600, Tampa, Florida, 33602, United States of America



**South Africa**

Mon - Fri  
9am - 5pm

+27 10 100 3589



**United Kingdom**

Mon - Fri  
9am - 5pm

+44 151 832 4300



**Netherlands**

Mon - Fri  
9am - 5pm

+31 40 798 7136



**Hong Kong**

Mon - Fri  
9am - 5pm

+852 3704 4979



**Australia**

Mon - Fri  
9am - 5pm

+61 7 3155 5555



**Spain**

Mon - Fri  
9am - 5pm

+37 822 112 079



**USA**

Mon - Fri  
9am - 5pm

+1 813 723 2225